

PAC30A-YT-40A SCR XIMADEN SERIES voltage regulator

SKU: 585195752827

Price: \$214.28

Categories: Relays

Tags: Ximaden

Product Link:

<https://www.electspares.com/product/pac30a-yt-40a-scr-ximaden-series-voltage-regulator/>

Product Description

PAC30A-YT-40A factory direct sales SCR Beijing XIMADEN XIMADEN SERIES voltage regulator

Additional Information

sort by color: PAC30A-YT-40A center is not grounded, PAC30A-YT-40A KR center is not grounded to speed up melting, PAC30A-YN-40A center ground, PAC30A-YN-40A KR center point grounding speeds up melting

Product Images



三相电力调整器>PAC30A系列欧式风格三相调功调压一体化电力调整器



说明:

1. 上述表格额定电流以纯阻负载为例, 如变压器负载或其他特殊负载, 请留更多裕量。
2. 出厂设置负载接线方式是中心不接地, 如需中心接地请订货时特殊说明。
3. 选件: 加模块电流控制XCT1 需特殊说明。

欧式风格的安全防尘结构, 美观大方。

红绿蓝色LED灯, 工作状态一目了然, 纯阻负载的可靠选择。

输入	手动给定信号	DC0-5V
	自动控制信号	(可根据客户需要调整)4-20mA, 输入阻抗120Ω; 采样时间) 50次/秒
	风机电源	220VAC 50HZ
输出	分辨率	调节输出0.2°
	输出电压	输入电压的0-95%
	控制方式	出厂默认为调压方式, 如要调压调功一体化订货时需特殊说明
	报警输出	继电器报警输出AL1、AL2报警接点, 容量240VAC 2A (纯阻)
	负载	三相380VAC 50HZ 纯阻/感性负载 1)星型中心不接地或外三角形 2)星型中心接地 3)三相半控整流桥
保护	缓起、缓停	缓起时间由内部电位器P3设定 (0.2-120秒) 缓关断时间固定3秒
	急停与自动缓启动	运行过程中瞬间缺相急停(<20ms), 加电后自动缓启动(三缺一相时被取消)
	超温保护	散热器温度高于80°C 禁止输出并报警。
	负载过流保护	报警并禁止输出(不能代替快速熔断器)
使用环境	安装环境	壁挂式垂直安装, 通风良好, 不受日光直射或热辐射, 无腐蚀性、无可燃性
	高度湿度	高温高湿以及海拔大于1000米, 应降额使用, 环境相对湿度: 90%
	温度	-10°C ~+55°C

型 号	标称电流	额定电流	尺寸mm	孔距	冷却方式
PAC30A-YT(N)-40A	40A	40A	170 × 130 × 210	Φ6mm 190 × 115mm	自然
PAC30A-YT(N)-40A+KR	40A	40A	270 × 130 × 210	Φ6mm 253 × 110mm	自然
PAC30A-YT(N)-60A	60A	50A	295 × 130 × 210	Φ6mm 288 × 110mm	风冷
PAC30A-YT(N)-60A+KR	60A	50A	310 × 130 × 210	Φ6mm 290 × 110mm	风冷
PAC30A-YT(N)-80A	80A	70A	295 × 130 × 210	Φ6mm 288 × 110mm	风冷

PAC30A-YT(N)-80A+KR	80A	70A	310 × 130 × 210	Φ6mm 290 × 110mm	风冷
PAC30A-YT(N)-120A	120 A	90A			
PAC30A-YT(N)-120A+KR	120A	90A			
PAC30A-YT(N)-150A	150A	95A			
PAC30A-YT(N)-150A+KR	150A	70A			



Scan for product details:

