

SHIMADEN Island Electric SR92 Intelligent PID Regulator

SKU: 26213084538

Price: \$14.29

Categories: Relays

Product Link:

<https://www.elecspares.com/product/shimaden-island-electric-sr92-intelligent-pid-regulator/>

Product Description

SHIMADEN Japan Shimaden SR92 intelligent PID regulator temperature and humidity controller temperature control meter multi-range SHIMADEN Island Electric SR92 Intelligent PID Regulator

Additional Information

sort by color: SR92-8I-N-90-100, SR92-8V-N-90-100, SR92-8P-N-90-100, SR92-8Y-N-90-100, SR92-6I-N-90-100, SR92-6P-N-90-100, SR92-6Y-N-90-100, Second output, RS485 communication, RS232 communication, Dual settings, Analog transmission output, remote control input, SR92-4Y-N-90-100, SR92-4I-N-90-100, SR92-4P-N-90-100, SR92-4V-N-90-100, SR92-6V-N-90-100, SR92-8Y-N-90-105, SR92-8I-N-90-140, SR92-8V-N-90-105, SR92-8P-N-90-108

Product Images



SR92 系列 代码选型表




项 目	代码	规 格			
1. 系 列	SR92-	72 × 72 DIN 尺寸 数字调节器			
2. 输 入	8	自由输入	热电偶	B, R, S, K, E, J, T, N, PL II, WRe5-26, (U, L (DIN43710))	
			测温电阻	Pt100 / JPt100	
			电压 (mV)	-10~10, 0~10, 0~20, 0~50, 10~50, 0~100mV DC	可编辑量程 (不可反向编辑量程) 范 围: -1999 ~ 9999 间 隔: 10 ~ 5000
	输入阻抗: 500 kΩ 以上				
4	电流 (mA)	0~20, 4~20 mA DC	接受阻抗: 250Ω		
6	电压 (V)	-1~1, 0~1, 0~2, 0~5, 1~5, 0~10V DC	输入阻抗: 500 kΩ 以上		
3. 调节输出 1	Y-	接 点	1a 接点容量: 240V AC 2A / 阻抗负载 比例周期: 1~120 秒		
	I-	电 流	4 ~ 20mA DC 负载阻抗: 600Ω 以下		
	P-	SSR 驱动电压	12V ±1.5V DC 30 mA 比例周期: 1~120 秒		
	V-	电 压	0~10V DC 负载电流: 2mA 以下		
4. 调节输出 2 (选件)	N-	无			
	Y-	接 点	1a 接点容量: 240V AC 2A / 阻抗负载 比例周期: 1~120 秒		
	I-	电 流	4~20mA DC 负载阻抗: 600Ω 以下		
	P-	SSR 驱动电压	12V ±1.5V DC 30 mA 以下 比例周期: 1~120 秒		
5. 电 源	V-	电 压	0~10V DC 负载电流: 2mA 以下		
	90-	100 ~ 240V AC ±10%	50/60Hz		
6. 事件输出, 加热器断线报警 (单相用) (选件)	08-	24V AC/DC ±10% 50/60Hz			
	0	无			
	1	事件输出	1a×2 点	接点容量: 240V AC 1A / 阻抗负载	调节输出 1 只有 Y, P 可选择
	2	事件+ 加热器断线报警 (30A CT 付带)			
3	事件+ 加热器断线报警 (50A CT 付带)				
7. 模拟输出 (选件)	0	无			
	3	0 ~ 10mV DC 输出阻抗: 10Ω			
	4	4 ~ 20mA DC 负载阻抗: 300Ω 以下			
	6	0 ~ 10V DC 负载电流: 2mA 以下			
8. 通讯功能, DI (外部控制输入) · 设定值偏移 (选件)	0	无			
	5	通讯功能	RS-485	连接台数最大31台	
	7		RS-232C	连接台数 1 台	
	DI (外部控制输出) 设定值偏移	8	设定值偏移 待机 控制特性 1 点 无电压接点输入 (集电极开路) 5V / 1mA		
0		无			
9. 特殊事项	9	有			

从代码选择表的各项目里选择一项。




外形图・面板开孔图

(单位: mm)




■ SR91 系列






■ SR92 系列



■ SR93 系列



■ SR94 系列



Scan for product details:

