

SR93 SHIMADEN temperature controller SR94 PID

SKU: 26211588822

Price: \$14.29

Categories: Relays

Product Link:

<https://www.electspares.com/product/sr93-shimaden-temperature-controller-sr94-pid/>

Product Description

SR93-8P-N-90-100SR94-8P-N-90-100, the last digit is the factory number and is not fixed regardless of the usage parameters, so you can ignore the last digit of the model when selecting.

SR93 Japanese Shimaden SHIMADEN original temperature and humidity controller SR94 temperature control table PID regulator

Additional Information

sort by color: SR93-6V-N-90-100, SR93-8P-N-90-100, SR93-8I-N-90-100, SR93-4I-N-90-100, SR93-8V-N-90-100, SR94-8P-N-90-100, SR93-8Y-N-90-100, SR94-8Y-N-90-100, SR94-4P-N-90-105, RS485 communication RS232 communication, SR94-8I-N-90-100, Dual settings, SR93-4Y-N-90-100, SR93-4P-N-90-100, SR93-4V-N-90-100, SR93-8I-Y-90-100, SR93-4I-N-90-105, SR93-8P-V-90-100R, SR93-4V-N-90-1480, SR94-4I-N-90-105, SR93-4Y-Y-90-140, SR93-8Y-N-90-105, SR93-8I-N-90-105, SR94-8Y-Y-90-100

Product Images



SR93/94 系列 代码选型表




项 目	代码	规 格			
1. 系列	SR93-	96 × 96 DIN 尺寸 数字调节器			
	SR94-	96 × 48 DIN 尺寸 数字调节器			
2. 输 入	8	自由输入	热电偶	B, R, S, K, E, J, T, N, PLⅡ, WRe5-26, {U, L (DIN43710)}	
			测温电阻	Pt100 / JPt100	
	4	电流 (mA)	电压 (mV)	-10~-10, 0~10, 0~20, 0~50, 10~50, 0~100mV DC 输入阻抗: 500 kΩ 以上	可编辑量程 (不可反向编辑量程) 范 围: -1999 ~ 9999 间 隔: 10 ~ 5000
			接受阻抗: 250Ω		
6	电压 (V)	-1~1, 0~1, 0~2, 0~5, 1~5, 0~10V DC 输入阻抗: 500 kΩ 以上			
3. 调节输出 1	Y-	接 点	1a 接点容量: 240V AC 2A / 阻抗负载 比例周期 1~120 秒		
	I-	电 流	4 ~ 20mA DC 负载阻抗: 600Ω 以下		
	P-	SSR 驱动电压	12V ±1.5V DC 30 mA 以下 比例周期: 1~120 秒		
	V-	电 压	0 ~ 10V DC 负载电流: 2mA 以下		
4. 调节输出 2 (选件)	N-	无			
	Y-	接 点	1a 接点容量: 240V AC 2A / 阻抗负载 比例周期 1~120 秒		
	I-	电 流	4~20mA DC 负载阻抗: 600Ω 以下		
	P-	SSR 驱动电压	12V ±1.5V DC 30mA 以下 比例周期: 1~120 秒		
	V-	电 压	0~10V DC 负载电流 2mA 以下		
5. 电 源	90-	100~240V AC ±10% 50/60Hz			
	08-	24V AC/DC ±10% 50/60Hz			
6. 事件输出, 加热器断线报警 (单相用) (选件)	0	无			
	1	事件输出 1a×2 点 接点容量: 240V AC 1A / 阻抗负载			调节输出 1 只有 Y, P 可选择
	2	事件 + 加热器断线报警 (30A CT 附带)			
	3	事件 + 加热器断线报警 (50A CT 附带)			
7. 选件	00	无			
	模拟输出	30	0~10mV DC 输出阻抗: 10Ω		
		40	4~20mA DC 负载阻抗: 300Ω 以下		
		60	0~ 10V DC 负载电流: 2mA 以下		
	DI (外部控制输入) 设定值偏移	08	设定值偏移, 待机, 控制特性 1 点 无电压接点输入 (集电极开路) 5V / 1mA		
		模拟输出 + DI (外部控制输入) 设定值偏移	38	0~10mV DC 输出阻抗: 10Ω 设定值偏移, 待机, 控制特性 1 点	
	48		4~20mA DC 负载阻抗: 300Ω 以下 设定值偏移, 待机, 控制特性 1 点		
	68		0~10V DC 负载电流: 2mA 以下 设定值偏移, 待机, 控制特性 1 点		
	通讯功能	05	RS-485 连接台数最大31台		
		07	RS-232C 连接台数 1 台		
8. 特殊事项	0	无			
	9	有			

从代码选择表的各项目里选择一项。




外形图・面板开孔图

(单位: mm)




■ SR91 系列






■ SR92 系列



■ SR93 系列



■ SR94 系列





Scan for product details:

