

SJ1738HA1 Sanju 110/120V Ball Bearing AC axial fan

SKU: 947048158050

Price: \$21.31

Categories: Fans

Tags: Sanju

Product Link:

<https://www.electspares.com/product/sj1738ha1-sanju-110-120v-ball-bearing-a-c-axial-fan/>

Product Description

The SANJUN SJ1738HA1 is a robust AC axial fan, precisely measuring 172mm x 152mm x 38mm, and featuring durable ball bearings for reliable operation. It functions on 110V to 120V AC power at both 50 Hz and 60 Hz frequencies. At 50 Hz, it draws 0.25A of current, consumes 30W of power, operates at 2850 RPM, and delivers 175 CFM of airflow with a static pressure of 0.65 inch H₂O, generating 54 dB(A) of noise. When running at 60 Hz, the fan draws 0.22A, consumes 24W, achieves 3400 RPM, provides 220 CFM of airflow with 0.75 inch H₂O static pressure, and produces 58 dB(A) of noise. This efficient fan weighs 760g and is engineered for effective air movement in various industrial cooling environments.

SJ1738HA1 Fan Parameters

Model: SJ1738HA1

Manufacturer: SANJUN

Type: AC Fan

Dimensions: 172 x 152 x 38 mm

Rated Voltage: 110-120V AC

Frequency: 50 Hz / 60 Hz

Rated Current (50Hz / 60Hz): 0.25A / 0.22A

Power Consumption (50Hz / 60Hz): 30 W / 24 W

Speed (50Hz / 60Hz): 2850 RPM / 3400 RPM

Airflow (50Hz / 60Hz): 175 CFM / 220 CFM

Static Pressure (50Hz / 60Hz): 0.65 inch H₂O / 0.75 inch H₂O

Noise Level (50Hz / 60Hz): 54 dB(A) / 58 dB(A)

Bearing Type: Ball Bearing

Weight: 760g

Product Images









Scan for product details:

