

# SJ9225HA1 SANJUN 110/120V AC Axial Fan

**SKU:** SJ9225HA1

**Price:** \$9.99

**Categories:** Fans

**Tags:** Sanju

**Product Link:**

<https://www.electspares.com/product/sj9225ha1-sanjun-110-120v-ac-axial-fan/>

---

## Product Description

---

The SANJUN SJ9225HA1 is an AC axial fan with dimensions of 92x92x25mm. It is designed to operate at two nominal voltages, 110VAC or 120VAC, with performance varying accordingly. At 110VAC, it draws 0.14A and consumes 15W, providing 68.0m<sup>3</sup>/h (40CFM) of airflow and generating 39.9Pa (0.16inchH<sub>2</sub>O) of static pressure, at a speed of 2300RPM and a noise level of 35dB(A). When operating at 120VAC, it draws 0.12A and consumes 10W, delivering 81.6m<sup>3</sup>/h (48CFM) of airflow and generating 52.3Pa (0.21inchH<sub>2</sub>O) of static pressure, at a speed of 2800RPM and a noise level of 37dB(A). This fan uses durable ball bearings, and its housing and impeller are both constructed from plastic. It is terminated with two wire leads.

SJ9225HA1 Fan Parameters

Manufacturer: SANJUN

Model: SJ9225HA1

Fan Type: AC Axial Fan

Dimensions: 92 x 92 x 25 mm

Rated Voltage: 110 VAC / 120 VAC

Current Rating: 0.14 A (at 110 VAC), 0.12 A (at 120 VAC)

Power Consumption: 15 W (at 110 VAC), 10 W (at 120 VAC)

Airflow: 68.0 m<sup>3</sup>/h (40 CFM) (at 110 VAC), 81.6 m<sup>3</sup>/h (48 CFM) (at 120 VAC)

Static Pressure: 39.9 Pa (0.16 inch H<sub>2</sub>O) (at 110 VAC), 52.3 Pa (0.21 inch H<sub>2</sub>O) (at 120 VAC)

Speed: 2300 RPM (at 110 VAC), 2800 RPM (at 120 VAC)

Noise Level: 35 dB(A) (at 110 VAC), 37 dB(A) (at 120 VAC)

Bearing Type: Ball Bearing

Termination: Two Wire Leads

Housing Material: Plastic

Impeller Material: Plastic

Weight: 0.23 kg

Application: This SANJUN AC axial fan is suitable for general cabinet cooling, power supply

ventilation, and various industrial or electronic applications requiring multi-voltage AC power.

## Product Images

---









---

Scan for product details:

